

### Panel components required:

<u>Component</u>	<u>Quantity/value/type</u>	<u>Function</u>	<u>Connect to:</u>	<u>Wire Kit type:</u>
Wire kit:	WK-10B	Board to panel wiring	All-see below	
Pots:	1xB50K	Lag/ slew amount	CF3D	3C
	2xC1M	Oscillator rate adjust	CF2D	3C
		Clock rate adjust	CF2B	3C
Switches:	1xSPDT	Sample/ track & hold select	CF5	3C-Black at notch
Jacks:	2xNormal	Clock out	CF3C	2C
		S/H out	CF4	2C
	2xSwitched	External signal in	CF3A	3C
		External clock in	CF3B	3C
LED's	2xColor of choice	Oscillator rate indicator	CF2C	2C
		Clock rate indicator	CF2A	2C

### Wire kit description WK-10B

<u>Qty</u>	<u>Cable</u>	<u>Connector description</u>	<u>Wires</u>
4	2C	3-pin MTA 0.100" socket	8" 24 AWG Red Pin 1 No wire Pin 2 8" 24 AWG Black Pin 3
6	3C	3-pin MTA 0.100" socket	8" 24 AWG Red Pin 1 8" 24 AWG White Pin 2 8" 24 AWG Black Pin 3

### PC Board connector conventions

